myprojectorlamps.com

The most trusted, dependable name in projector lamp sales.

http://www.myprojectorlamps.com

http://www.myprojectorlamps.ca

http://www.myprojectorlamps.eu

The following projector manual has not been modified or altered in any way.

PLUS

DATA PROJECTOR

V3-131/V3-111

User's Manual

IMPORTANT

* DLP™ (Digital Light Processing) and DMD (Digital Micromirror Device) are registered trademarks of Texas Instruments Incorporated (U.S.A.).
* DMD is an ultra-precise part developed by Texas Instruments (U.S.A.) which takes the place of liquid crystal (in the projector).
* VGA and XGA are trademarks or registered trademarks of International Business Machines Corporation (U.S.A.).
* S-VGA is a registered trademark of Video Electronics Standards Association.
* Microsoft, Windows, and PowerPoint are registered trademarks of Microsoft Corporation (U.S.A. and other countries).
* Macintosh is a trademark of Apple Computer Inc. (U.S.A.).

Note that even in the absence of explanatory notes, serious attention is paid to the trademarks of the various companies and to the product trademarks.

IMPORTANT SAFETY INFORMATION

Precautions

Please read this manual carefully before using your PLUS Data Projector and keep the manual handy for future reference.

These operating instructions apply to both models V3-131 and V3-111.
The two models are identical in appearance but have different display resolutions and projection distances.

⚠ CAUTION

TO PREVENT SHOCK, DO NOT OPEN THE CABINET. NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED PLUS SERVICE PERSONNEL.

⚠	This symbol warns the user that uninsulated voltage within the unit may have sufficient magnitude to cause electric shock. Therefore, it is dangerous to make any kind of contact with any part inside of this unit.
⚠	This symbol alerts the user that important literature concerning the operation and maintenance of this unit has been included. Therefore, it should be read carefully in order to avoid any problems.

The above cautions are given on the bottom of the product.

WARNING

TO PREVENT FIRE OR SHOCK, DO NOT EXPOSE THIS UNIT TO RAIN OR MOISTURE. DO NOT USE THIS UNIT'S GROUNDED PLUG WITH AN EXTENSION CORD OR IN AN OUTLET UNLESS ALL THREE PRONGS CAN BE FULLY INSERTED. DO NOT OPEN THE CABINET. THERE ARE HIGH-VOLTAGE COMPONENTS INSIDE. ALL SERVICING MUST BE DONE BY QUALIFIED PLUS SERVICE PERSONNEL.

Hg: Lamp in This Product Contains Mercury. Dispose of Lamp According to Local, State or Federal Law.

WARNING

This is a class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures.

RF Interference

WARNING

The Federal Communications Commission does not allow any modifications or changes to the unit EXCEPT those specified by PLUS Vision in this manual. Failure to comply with this government regulation could void your right to operate this equipment.
This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

DOC Compliance Notice

This Class A digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

Important Safeguards

These safety instructions are to ensure the long life of the unit and to prevent fire and shock. Please read them carefully and heed all warnings.

Installation

- For best results, use the unit in a darkened room.
- Place the unit on a flat, level surface in a dry area away from dust and moisture.
- Do not place the unit in direct sunlight, near heaters or heat radiating appliances.
- Exposure to direct sunlight, smoke or steam can harm internal components.
- Handle the unit carefully. Dropping or jarring can damage internal components.
- Do not place heavy objects on top of the unit.

Power Supply

- The unit is designed to operate on a power supply of 100 - 240 V 50/60 Hz AC. Ensure that your power supply fits these requirements before attempting to use the unit.
- Handle the power cable carefully and avoid excessive bending. A damaged cord can cause electric shock or fire.
- Disconnect the power cable (mains lead) from the power outlet after using the unit.
  Before disconnecting the power cable, make sure that the STANDBY indicator lights in amber (not blinking or in green).

Cleaning

- Disconnect the power cable (mains lead) from the unit.
- Clean the cabinet of the unit periodically with a damp cloth. If heavily soiled, use a mild detergent. Never use strong detergents or solvents such as alcohol or thinner.
- Use a blower or lens paper to clean the lens, and be careful not to scratch or mar the lens.
- Clean the ventilation slots and speaker grills on the unit periodically using a vacuum cleaner. If accumulated dust blocks the ventilation slots, the unit will overheat, which may cause the unit to malfunction.
  Use a soft brush attachment when using the vacuum cleaner. Do not use a hard attachment, such as a crevice tool, to prevent the damage to the unit.

Lamp Replacement

- Be sure to replace the lamp when the Status indicator comes on. If you continue to use the lamp after 2000 hours of usage, the lamp will turn off.

Fire and Shock Precautions

- Ensure that there is sufficient ventilation and that vents are unobstructed to prevent the buildup of heat inside the unit. Allow at least 10 cm (4 inches) of space between the unit and walls.
- Prevent foreign objects such as paper clips and bits of paper from falling into the unit. Do not attempt to retrieve any objects that fell into the unit. Do not insert any metal objects such as a wire or screwdriver into the unit. If something should fall into the unit, immediately disconnect the power cable from the unit and have the object removed by a qualified PLUS service person.
- Do not place any liquids on top of the unit.

Carrying around

When carrying the unit around, please use the storage case that comes with it and, to protect the lens from scratches, always shut the sliding lens shutter. Also, do not subject the unit to strong mechanical shock.

CAUTION – HOT!

The area around the exhaust vents is hot during and immediately after image projection.
To avoid burns, keep your hands away from this area.
Wait until the exhaust vents area cools off before touching it.

Do not look into the lens while the unit is on. Serious damage to your eyes could result.

Major Features

World's thinnest projector – just 35 mm thick

Plus is seeing just how thin the projector can be made. With our retractable lens and other unique ideas and technologies, we have developed a projector just 35 mm thick, something previously considered impossible.

Designed for portability

The flat design allows the projector to fit in a regular business bag along with documents and a laptop. Thanks to the sliding type lens shutter, the lens is protected without any parts jutting out.

Sharp, clear picture

The DLP™ display system affords RGB color fidelity and inconspicuous gaps between the individual dots, thereby permitting the display of small characters and diagrams with distinct clarity.

High contrast ration of 2000:1

Use of a new generation of DMD devices has given birth to an amazing 2000:1 high contrast ratio.
By widening the difference of brightness between black and white, you can see a degree of sharpness that is greater than just the brightness based on specifications.

Powerful functions for presentations

A wide variety of easy-to-set functions have been built into the projector, from a digital keystone correction function (used when making settings) that corrects picture distortion, to an auto adjustment function that automatically identifies the PC signal.
There is also a built-in "Presentation Timer" function for further presentation convenience.

Great moving image playback capabilities using the same principles as DLP Cinema technology

Plus DLP type projectors have the same makings as the DLP Cinema technology used in movie theaters. Because of their extremely fast response, even images with much movement – sports, movies – play smoothly without blurring.

Security lock function

The lock can be set so that a password must be input when the projector is started up. Without the correct password, no operations other than turning the power on and off can be performed. This function effectively protects the projector from unauthorized use.

Eco-mode switch function for the lamp output

Using the lamp Eco-mode will extend the life of the lamp and lower the power consumption.
By switching the lamp mode to suit your operating environment, you will save on lamp cost as well as contribute to energy conservation and ecology.

Table of Contents

IMPORTANT SAFETY INFORMATION **E-2**
Major Features **E-4**
Table of Contents **E-5**
Checking the Supplied Accessories **E-7**
Names of the Main Unit Parts **E-9**
Names of the Remote Control Parts **E-11**
Preparing the Remote Control **E-12**
Button Battery Replacement E-12
Remote Control Range E-12
The Procedure Up to Projecting to the Screen **E-13**
Placement Guide **E-14**
V3-131 Screen Size and Projection Distance E-14
V3-111 Screen Size and Projection Distance E-15
Connecting Personal Computers and Video Equipment **E-17**
Connections with Personal Computer E-17
Connect the projector's RBG connector using the included RGB signal cable. .. E-17
To Output the External Output Signal of a Notebook Computer E-18
Connections with Composite Signals E-19
Video Equipment with VIDEO Connectors E-19
Video Equipment with S-VIDEO Connectors E-19
Connections with Component Signals E-20
When the Video Equipment Has a YCbCr Connector or YPbPr Connector E-20
Connections with the AUDIO Jack E-21
Power Cable Connections and Switching the Power On/Off **E-22**
Operating E-22
Finishing E-24
Adjustment of the Projection Screen **E-25**
Adjustment of the Projection Screen E-25
Making Adjustments with the Adjusters E-26
General Operation **E-27**
Input Selection E-27
Automatic Adjustment E-27
Selection of Aspect Ratio E-28
Freezing a Moving Picture E-29
Cancelling Video and Audio Temporarily E-29
Lamp Mode E-29
Keystone E-30
Adjustment of the Volume E-30
Enlargement of the Image and Video Movement E-31
Using the Presentation Timer E-32
Protecting the Projector with the Security Lock E-33
Using the Quick Menu E-35
Menu Operation Method **E-36**
Performing Menu Operations E-38
List of Item Names Offering Input Selection and Adjustments/Settings E-41
Image **E-43**
Brightness / Contrast / Color / Tint / Sharpness E-43
Picture Adj. / Fine Picture / H Position / V Position E-43
Reset E-44
Color **E-45**
Quick Color Adj. E-45
Gamma E-45
Color Temp. E-46
White E-46
Color Space E-46
White Balance E-47

View **E-48**
Aspect E-48
Filter E-48
Vertical Flip E-49
Keystone E-49
Keystone Save E-49
Setup **E-50**
Auto Source E-50
Auto Power Off E-50
Menu Position E-51
Lamp Mode E-51
Input Format E-52
Presentation Timer E-52
Option **E-53**
Language E-53
On Screen E-53
Background E-53
Startup Screen E-54
Security Lock E-54
Info. **E-55**
Status E-55
Factory Default E-55
Lamp Timer Reset E-55
Resolution / Frequency E-56
Lamp Timer E-56
When an Indicator is Lit or Flashing **E-57**
Troubleshooting **E-59**
Cleaning **E-60**
Replacing the Lamp Cartridge **E-61**
Specifications **E-64**
Table of Supported Frequency **E-65**
Cabinet Dimensions **E-66**

Checking the Supplied Accessories

Remove the main unit and the accessories from the box and check that the following items are included.

Wireless remote control unit
(includes one button battery) [1]
This controls the projector. Please remove the transportation insulation sheet at time of purchase. (See Page E-12.)



Power cable (1.8 m / 5.9 feet) [1]
This power cable supplies power to the unit. See Page E-22 about connections.



RGB signal cable
(Mini D-sub 15-pin, 2 m / 6.6 feet) [1]
This is used in making connections with a personal computer. See Page E-17 about connections.
No. 773711000



User's Manual (CD-ROM edition) [1]
User's Manual (Simplified Edition) [1]



Storage case [1], Cable case [1]
These cases are designed to hold the projector itself and its accessories.
Use them when storing the projector.



HOW TO PUT THE PROJECTOR INTO THE STORAGE CASE
Lower the projector's lens unit and close the lens shutter before storing the projector in the case. See Page E-9.
Place the accessories in the cable case.





Expendables and Options



V3 Series lamps
Model V3-120 (ordering code: 28-051)

"WARNING"

Handling the cables supplied with this product, will expose you to lead, a chemical known to the State of California to cause birth defects or other reproductive harm.
Wash hands after handling.

Names of the Main Unit Parts



Handling the Lens Unit

When using the projector

① Slide the lens shutter to the left until it stops.
② Press the lift button (marked “PUSH”).
The lens unit rises and projecting is now possible.



When storing the projector

① Press on the top surface of the lens unit to lower it until you feel it click.
② Slide the lens shutter to the right to close it.





STANDBY indicator [E-22, 57]

STANDBY STATUS

STATUS indicator [E-29, 57]

STANDBY

STANDBY button [E-22]

AUTO

AUTO button [E-27]

SOURCE

SOURCE button [E-27]

Remote control sensor [E-12]

AC IN connector [E-22]

Ventilation slot

Ventilation slots

Built-in security slot
(See description below.)

RGB connector [E-17, 20]

AUDIO S-VIDEO VIDEO RGB

VIDEO connector [E-19]

S-VIDEO connector [E-19]

AUDIO connector [E-21]

Built-in Security Slot

This security slot supports the MicroSaver Security System manufactured by Kensington Microware Inc.

Names of the Remote Control Parts



Infrared transmitter [E-12]

STANDBY button [E-22, 24]
This button is used to switch ON the power and set the unit to the STANDBY mode.

Buttons used for input selection [E-27]
RGB button and VIDEO button (VIDEO / S-VIDEO)

MUTE button [E-29]
(Temporarily cancels the video and audio)

Number buttons [E-33]
(Used for the security lock.)

FREEZE button [E-29]
(Freezes moving pictures)

VOL button [E-30]
(Volume adjustment)

KSTN button [E-30]
(Keystone correction adjustment)



Buttons used for menu operations [E-36]
The ▲, ▼, ◀ and ▶ buttons are the select (▲, ▼, ◀ and ▶) buttons.

QUICK button [E-35]
(Displays a simplified menu)

ECO button [E-29]
(Selection of lamp mode)

AUTO button [E-27]
(Automatic adjustment of the RGB moving image)

ASPECT button [E-28]
(Selects the vertical and horizontal ratio of the screen)

TIMER button [E-32]
(Presentation timer time setting display)

ZOOM button [E-31]
(Digital zoom adjustment)

Precautions

Handling of the Remote Control

* Do not drop the remote control or handle it inappropriately.
* Do not expose the remote control to water or other liquids. Should the remote control become wet, wipe it dry immediately.
* Try to avoid use in hot and/or humid locations.
* Please keep button battery out of the reach of children. If a battery is swallowed, promptly obtain the medical care of a doctor.
* Remove the battery from the remote control when it is not going to be used for a long period.
* Some operations (such as menu operations) are available only through the use of the remote control and attention should be given to its careful handling.

Preparing the Remote Control

Button Battery Replacement

Using the remote control for the first time

The battery compartment is fitted with a transportation insulation sheet at the time of shipping. Pull out the sheet and remove it. The remote control is now ready for use.



Replacement Method

1 **(A) With the knob pressed to the right side, (B) draw out the battery case.**



2 **Remove the old battery and install a new button battery with (+) side facing upward in the battery holder.**



Purchase a CR2025 type battery for replacement.

3 **Insert the battery holder into the remote control and push in until the battery holder closes with a "click" sound.**



CAUTION
Danger of explosion if battery is incorrectly replaced.
Replace only with the same or equivalent type (CR2025) recommended by the manufacturer.
Dispose of used batteries according to your local regulations.

Remote Control Range

Point the infrared transmitter of the remote control toward the remote control sensor located at the front or rear of the main unit and operate.
Reception of the remote control signal should generally be possible within the range illustrated below.





Top View

Note
- *Exposure of the main unit's remote control sensor or the remote control infrared transmitter to bright light or the obstruction of the signal by an obstacle located in the pathway may prevent operation.*
- *The remote control will not function when the battery is exhausted.*

The Procedure Up to Projecting to the Screen

Perform setup adjustments in the following order.

1 Position the projector

Determine the locations to set up the screen and the projector.
See “Placement Guide” on Page E-14.

2 Connect the video equipment and personal computer

Connect your equipment to the projector.
When making connections with the personal computer’s RGB connector, see “Connections with Personal Computer” on Page E-17.

When making connections with the video equipment’s video connector or an S-video connector, see “Connections with Composite Signals” on Page E-19.

When making connections with the video equipment’s YCbCr connector or YPbPr connector, see “Connections with Component Signals” on Page E-20.

When playing the audio through the built-in speaker of the projector, see “Connections with the AUDIO Jack” on Page E-21.

3 Connect the power cord, open the lens shutter and raise the lens unit.

See “Operating” on Page E-22.
See “Finishing” on Page E-24.

4 When selecting the language of menu displays, etc.

(Only when the power is first switched on following purchase)
See “When [Menu Language Select] is Displayed Upon Switching On the Power” on Page E-23.

5 Switching on the power of the personal computer and video equipment

6 Properly adjust the projection image to the screen

See “Adjustment of the Projection Screen” on Page E-25.

7 Selecting input equipment

See “Input Selection” on Page E-27.

8 Adjust the screen or video image

Adjust the image to the optimum condition as required.
See the Table of Contents for the adjustment items.

About DLP projectors

Though careful attention is paid to providing optimum quality, please note that with DLP type projectors, in rare cases there may be black spots or bright spots among the picture elements.

Note:
* *Please purchase a screen.*
* *A component cable (order code 28-690), which is available separately, is required to connect a DVD player or other equipment with YCbCr connectors.*
* *A component cable (order code 28-690), which is available separately, is required to connect high definition (HD) video equipment or other equipment with YPbPr connectors.*

Placement Guide

- **Use this information as a guide to find out about the screen size when the projector is placed at a certain location, or to find out the approximate size of a screen that will be required.**
- **Refer to the projection distance table for your projector model.**
- **When installing the projector on its back, change the projection method. See "Vertical Flip" on page E-49.**

V3-131 Screen Size and Projection Distance

- **The projection distance over which focussing is adjustable is 1.20 m (3.94 feet) to 10.00 m (32.81 feet). The projector should be placed within this range.**



Screen Size Designation (Inches)	Screen Size Width x Height		Projection Distance		Height h1		Height h2	
	(m)	(feet)	(m)	(feet)	(m)	(feet)	(m)	(feet)
36"	0.73×0.55	2.40 × 1.80	1.20	3.94	0.65	2.13	0.10	0.33
40"	0.81×0.61	2.67 × 2.00	1.33	4.36	0.72	2.36	0.11	0.36
60"	1.22×0.91	4.00 × 3.00	2.00	6.56	1.07	3.51	0.16	0.52
80"	1.63×1.22	5.33 × 4.00	2.67	8.76	1.44	4.72	0.22	0.72
100"	2.03×1.52	6.67 × 5.00	3.33	10.93	1.79	5.87	0.27	0.89
120"	2.44×1.83	8.00 × 6.00	4.00	13.12	2.15	7.05	0.32	1.05
150"	3.05×2.29	10.00 × 7.50	5.00	16.40	2.69	8.83	0.40	1.31
180"	3.66×2.74	12.00 × 9.00	6.00	19.69	3.22	10.56	0.48	1.57
200"	4.06×3.05	13.33 ×10.00	6.67	21.88	3.59	11.78	0.54	1.77
250"	5.08×3.81	16.67 ×12.50	8.33	27.33	4.48	14.70	0.67	2.20
300"	6.10×4.57	20.00 ×15.00	10.00	32.81	5.38	17.65	0.81	2.66

* There is a tolerance of ±5% due to design values.
* This table uses the lens apex and lens center as references and requires that the projector be in a horizontal condition (with front and rear adjusters fully withdrawn).

V3-111 Screen Size and Projection Distance

- **The projection distance over which focussing is adjustable is 1.20 m (3.94 feet) to 12.82 m (42.06 feet). The projector should be placed within this range.**



Screen Size Designation (Inches)	Screen Size Width x Height		Projection Distance		Height h1		Height h2	
	(m)	(feet)	(m)	(feet)	(m)	(feet)	(m)	(feet)
28"	0.57×0.43	1.87 × 1.40	1.20	3.94	0.59	1.94	0.16	0.52
40"	0.81×0.61	2.67 × 2.00	1.71	5.61	0.83	2.72	0.22	0.72
60"	1.22×0.91	4.00 × 3.00	2.56	8.40	1.25	4.10	0.34	1.12
80"	1.63×1.22	5.33 × 4.00	3.42	11.22	1.67	5.48	0.45	1.48
100"	2.03×1.52	6.67 × 5.00	4.27	14.01	2.08	6.82	0.56	1.84
120"	2.44×1.83	8.00 × 6.00	5.13	16.83	2.50	8.20	0.67	2.20
150"	3.05×2.29	10.00 × 7.50	6.41	21.03	3.13	10.27	0.84	2.76
180"	3.66×2.74	12.00 × 9.00	7.69	25.23	3.75	12.30	1.01	3.31
200"	4.06×3.05	13.33 ×10.00	8.55	28.05	4.17	13.68	1.12	3.67
250"	5.08×3.81	16.67 ×12.50	10.68	35.04	5.21	17.09	1.40	4.59
300"	6.10×4.57	20.00 ×15.00	12.82	42.06	6.25	20.51	1.68	5.51

* There is a tolerance of ±5% due to design values.
* This table uses the lens apex and lens center as references and requires that the projector be in a horizontal condition (with front and rear adjusters fully withdrawn).

Installation Height of Projection Screen [Reference]
Once the installation location and position have been decided, the projection height should be checked. In the case of large screen sizes, there are instances where the image cannot be projected within the floor to ceiling height.
The required installation height can be found using the following formula:
[Height from center of lens to top edge of the projection(h1)] m (feet) + 0.03m (0.1 feet) + Stand height

Example:
Using a 150" 4:3 screen and placing the projector horizontally, the required installation height will be
3.13m (10.3 feet) + 0.03m (0.1 feet) = 3.16m (10.4 feet) (without a stand)
An installation room with a height of 2.4m (7.9 feet) will have insufficient room height even when the projector is placed on the floor. (The rear adjusters can be extended to lower the projected image.)



Connecting Personal Computers and Video Equipment

Connecting this unit with a personal computer permits presentation data to be projected as a large screen display at conferences, lectures, and on other occasions. Furthermore, connecting this unit to a DVD player or other video equipment source in combination with an audio/video amplifier and speaker system will allow you to enjoy convincing home theater.

Connections with Personal Computer

Please check the following before making connections with the personal computer.

- A suitable resolution for the V3-111 is 800 × 600 dots (S-VGA) and the maximum displayable resolution is XGA (1024 × 768 dots).
- A suitable resolution for the V3-131 is 1024 × 768 dots (XGA) and the maximum displayable resolution is S-XGA (1280 × 1024 dots).
  Make changes to a displayable resolution at the personal computer side. Please check with "Table of Supported Frequency" on Page E-65.
- The setting method for the personal computer will differ depending on the specific model. Please read the personal computer instruction manual or the on-line help information, or contact the manufacturer of your personal computer.

Connect the projector's RBG connector using the included RGB signal cable.

- When making connections with the RGB connector of the projector, please make the connection via the supplied RGB signal cable.
- The projector has been set to "Auto" at the factory; however, if it does not project, please change the input setting to "RGB" using the menu sequence of [Setup] → [Input Format] → [RGB].
  See "Input Format" on Page E-52.



Note:

- ** Before making connections, check the power of the projector and the equipment to be connected is switched off.*
- ** When projection will be with a notebook computer connected, knowledge will be required for the cable connection and notebook computer startup procedure as well as the operation that follows startup. Please consult the instruction manual of your notebook computer or the on-line help.*

To Output the External Output Signal of a Notebook Computer

When projection will be with a notebook computer connected, knowledge will be required for the cable connection and notebook computer startup procedure as well as the operation that follows notebook startup. Please consult the instruction manual of your notebook computer or the on-line help while performing the following procedure.

1 Check whether a signal is being sent from the notebook computer to the projector.
An indication appearing on the liquid crystal display of the notebook computer does not necessarily mean that an external output signal is being output.
REFERENCE: When “Resolution” or “Frequency” is not displayed under “Info.” on the menu of the projector, this means that the external output signal is not being output from the personal computer. See “Resolution/Frequency” on Page E-56.

2 Should a sign not be output from the notebook computer, please try the operation described below.
For an IBM PC/AT compatible computer, press the [Fn] key plus any one of the [F1] to [F12] keys. (See the table below.)

Manufacturer	Model	Key
akia	All computers	Fn + F2
COMPAQ	All computers	Fn + F4
DELL	All computers	Fn + F8
EPSON	All computers	Fn + F8
FUJITSU	All computers	Fn + F10
GATEWAY	All computers	Fn + F3
iiyama	All computers	Fn + F3
IBM	All computers	Fn + F7
NEC	All computers	Fn + F3
Panasonic	All computers	Fn + F3
SHARP	All computers	Fn + F5
SONY	All computers	Fn + F7
SOTEC	All computers	Fn + F3
TOSHIBA	All computers	Fn + F5
Victor	All computers	Fn + F10

Note: Table information is current to September 2002.

Note:
When the liquid crystal display of the notebook computer and the projector are displayed at the same time, the projected image might not be correct even though the liquid crystal display shows a correct indication. Should this occur, stop the simultaneous display of the notebook computer and try the mode with external output only. Try an operation such as that described in aforementioned Step 2 and try closing the liquid crystal panel which might result in external output only.

Connections with Composite Signals

Video Equipment with VIDEO Connectors

- Connect to the projector's VIDEO connector using a commercially available video cable.
- The input setting of the VIDEO connector has been set to "Auto" at the factory; however, if the projector does not project, please change the input setting to "Your Country's Television Broadcast System" using the menu sequence of [Setup] → [Input Format] → [Video].
  See "Input Format" on Page E-52.

Video Equipment with S-VIDEO Connectors

- Connect to the projector's S-VIDEO connector using a commercially available S-Video cable.
- The input setting of the S-VIDEO connector has been set to "Auto" at the factory; however, if the projector does not project, please change the input setting to "Your Country's Television Broadcast System" using the menu sequence of [Setup] → [Input format] → [S-Video].
  See "Input Format" on Page E-52.



Connections with Component Signals

When the Video Equipment Has a YCbCr Connector or YPbPr Connector

- The projector has been set to “Auto” at the factory; however, if it does not project, please change the input setting to “Component” using the menu sequence of [Setup] → [Input Format] → [RGB].
  See “Input Format” on Page E-52.
- When projecting the YCbCr signal or YPbPr signal, if the color of the overall image strongly leans toward being greenish or another color, change the setting under the menu of [Color] → [Color Space].
  See “Color Space” on Page E-46.



Connections with the AUDIO Jack

* Connect to the projector's AUDIO jack using a commercially available audio cable. If the other device has an RCA phono type audio jack, connect via a commercially available audio converter cable.
* The built-in speaker of the projector provides monaural audio. To enjoy convincing audio reproduction, please connect the audio output of the video equipment to your audio system.
* The built-in speaker outputs the audio of the equipment connected to the AUDIO jack.



Power Cable Connections and Switching the Power On/Off

There is an order in which the power cable is connected and the power is switched on/off.

Operating

1 Connect the AC IN connector of the projector and the power outlet using the supplied power cable.
The STANDBY indicator will light in amber, and the unit will enter the standby mode.



2 ① Slide the lens shutter to the left until it stops.
② Press the lift button (marked "PUSH").
The lens unit rises and projecting is now possible.

3 Switch on the projector power
Press the STANDBY button.

STANDBY **(button on main unit)**



> ***Note:***
> *The power will not turn on unless the lens unit is raised.*
> *If the STANDBY button is pressed when the lens is stowed away, the STATUS and STANDBY indicator's flash orange for several seconds to notify you that the lens is not raised.*

The first time the power is switched on after purchase, [Menu Language Select] will be displayed. See Page E-23 for information about language selection.

- When the power is turned on, the STANDBY indicator starts flashing green, then stops flashing after about 60 seconds. If the STATUS indicator lights green at this time, the lamp mode is set to "Eco". See E-29 and 51 for instructions on selecting.
- If the power does not come on, see "When the STATUS Indicator is Lit or Flashing" on Page E-57.

This indicator is also lit green in Eco-mode.



If the "Password" input window is displayed: See E-34.
A password is set for this projector.
The projector cannot be used unless the correct password is input.
To turn off the power: See E-24.

The projector is now capable of regular projection.

4 Switch on the power of the connected equipment

> ***Note:***
> - *When the power plug will be unplugged from the power outlet, please place the projector near the power outlet so that it may be reached easily.*
> - *Press the STANDBY button after the STANDBY indicator is lit in amber.*

When [Menu Language Select] is Displayed Upon Switching On the Power

The first time the power is switched on after purchase, [Menu Language Select] will be displayed. Follow the procedure described below and select the display language of the projector.
If the image is blurred, turn the focus ring counterclockwise or clockwise to focus it. See Page E-25.



1 **Press the SELECT ▲▼ buttons of the Remote control and align the deep blue cursor with [English].**





2 **Press the ENTER button to set.**
This will set the language and [Menu Language Select] will close.



This completes the selection of the display language.

Caution:
[Menu Language Select] will not appear the next time the power is switched on.
Should a change of language become necessary, see "Language" on Page E-53.

Finishing

1 Switch off the power of the connected equipment

2 Switch off the power of the projector

Press the STANDBY button.

STANDBY **(button on main unit)**



The [Power Off] display appears.
When the level gauge reaches maximum, the projection screen will go off (in about 5 seconds) and the projector will enter the power-off operation.



> ***Note:***
> *Do not stow away the lens unit while projecting an image. Doing so could damage the projector. If the lens unit has been stowed away while projecting an image, the STATUS and STANDBY indicator's flash orange and the projector is automatically turned off.*

> ***Note:***
> * *The operation can be cancelled by pressing a button other than the STANDBY button.*
> * *One more press of the STANDBY button will switch off the power.*

The STANDBY indicator changes to flashing amber and lights a steady amber after about 90 seconds (when the unit enters the standby mode).



3 Unplug the power cable

Check that the STANDBY indicator is lit in amber and then unplug the power cable.
The STANDBY indicator will go off when the power cable is unplugged.

4 ① Press down on the lens unit until a "click" is heard and the lens unit locks.
② Slide the lens shutter to the right to close it.



> **Warrning**
> Do not unplug the power cable while the STANDBY indicator is flashing amber. Doing so may shorten the life of the lamp or damage the projector.

Adjustment of the Projection Screen

Switch on the power of the connected equipment and make the adjustments with the video signal being input to the projector.

Adjustment of the Projection Screen

1 Adjust the projection image to the screen.

Check that the screen is set level and vertically.

(1) If the image is shifted to the left or right, move the main unit horizontally. (Align the center of the screen and the center of the projector lens.)

(2) If the image is shifted vertically, move the image up or down with the adjuster. See “Making Adjustments with the Adjusters” on Page E-26.

(3) If the image is slanted, adjust by turning the right or left adjuster. See “Making Adjustments with the Adjusters” on Page E-26.

(4) A projection image such as that illustrated in the diagram is the result of the projector not being perpendicular to the screen. Set the projector so that it is pointing straight toward the screen.

(5) If the image shows keystone distortion, adjust using remote control or menu operations. See “Keystone” on Page E-30, 49.



2 Turn the focus ring and adjust the focus of the screen





Making Adjustments with the Adjusters

Raising the projection image

While viewing the projection image, (1) press and hold the front adjuster buttons located at the left and right and, (2) raise the projector to align the image with the screen, then release your fingers.

Turn the left and right front adjusters for fine adjustment. Adjust so that there is no shaking of the projector.



Lowering the projection image

Use the procedure described above to lower the front adjusters.

If the rear adjusters are turned to lift the rear, the projected image lowers.

Adjust so that there is no shaking of the projector.



Note:

When the projector has a rear installation is used, the orientation of the projection will need to be changed.
Please see “Vertical Flip” on Page E-49.

General Operation

This section describes the use of direct operation with the main unit or remote control buttons.
For information about operation using the menu, see "Menu Operation Method" on Page E-36 and the various items on Pages E-43 to E-56.

Input Selection

This operation selects the input signal to be projected.



Main unit operation: Press the SOURCE button.
(It will not function while the menu or the quick menu is displayed.)

When Auto Source is On
Whenever the SOURCE button is pressed, the projector automatically selects another source that has the next input signal.

When Auto Source is Off
The input selection condition used last time will be set.
Each press of the button moves the selection one step in the sequence of RGB → VIDEO → S-VIDEO. Note that the various input signals will become the signal type set with [Input Format] See "Input Format" on page E-52.

Remote control operation: Press the desired input selection button.
RGB button ..... Switches the RGB input.
VIDEO button ..... The input switches between VIDEO and S-VIDEO each time the button is pressed.



When Auto Source is On
When an input signal is not present at the selected source, the projector automatically selects the next source that has an input signal.

When Auto Source is Off
The projector switches to the selected source regardless of whether an input signal is present.

> ***Note:***
> * *When you do not operate source selection, the projector will assume the input selection condition that was previously used.*
> * *See "Auto Source" on Page E-50 for information about the Auto Source on and off conditions.*

Automatic Adjustment

This function automatically adjusts the position shift, screen size, vertical stripes, and color infidelity of the projected analog RGB input signal.
Normally automatic adjustment is performed at the time of signal selection.



Main unit operation/Remote control operation: Press the AUTO button.
(This will not function while the menu or the quick menu is displayed.)
A press of the AUTO button starts the automatic adjustment.

> ***Note:***
> * *If the display position is shifted, vertical lines appear on the picture, or the projection is not good even after using automatic adjustment, please perform image adjustment manually. See "Picture Adj. / Fine Picture / H Position / V Position" on Page E-43.*
> * *When the image extends beyond the boundaries of the screen or is smaller than the screen, set Aspect to "Auto". See "Selection of Aspect Ratio" on Page E-28 and "Aspect" on Page E-48.*



Selection of Aspect Ratio

This function selects horizontal and vertical picture proportions of the input signal.

Press the ASPECT button while viewing the projected image and select the aspect ratio.



Personal Computer Signal
Each press of the ASPECT button advances the selection one step in the sequence of Auto → Direct → Real, and then repeats.

Auto ..... Automatically enlarges or reduces the image to project a full screen in a ratio of 4:3
Direct ..... Maintains the aspect ratio and projects a picture of the maximum displayable size
Real ..... Projects the input signal without pixel conversion.



Video Signals / Component Signals
Each press of the ASPECT button advances the selection one step in the sequence of Auto → Wide → Zoom, and then repeats.

Auto ..... While maintaining the aspect ratio, projects a full screen so that no portions extend beyond the boundaries of the screen. The top and bottom of the 16:9 image becomes black.
Wide ..... Projects to fill the full width with the entire image at 16:9.
(This feature is used to project a squeezed image in a proper aspect ratio.)
Zoom ..... Projects only the 4:3 portion within 16:9 image to fill the screen.
(Portion that extend off screen is cut.)



Note:
When selection has been made for the "Real" setting of the personal computer signal (i.e., when the input signal and the projector display resolution are high) and the "Zoom" setting of the video signal, pressing the SELECT ▲▼◀▶ buttons on the remote control will permit movement of the display position. Note that there will not be any movement when the menu or the quick menu is displayed.

Freezing a Moving Picture

This function is used to stop and view a moving picture. Note that the input image continues to advance even though the picture there is a still picture condition.

A press of the FREEZE button changes the screen to a still picture. A further press returns the screen to a moving picture.



Cancelling Video and Audio Temporarily

This function is used to cancel the video and audio at the same time.

A press of the MUTE button will blank the picture and the sound, and the screen will take on the background color that has been set. Another press will cause a return to the original conditions.



Lamp Mode

Use this if the picture is projected on a small screen and the picture is too bright or when projecting images in dark rooms.

Pressing the ECO button will set the lamp mode.

Eco (STATUS indicator is lit green)
The lamp's brightness is reduced to approximately 80%, extending the lamp's service life.

Normal (STATUS indicator is off)
The lamp brightness is set to 100% and the screen is bright.

> ***Note:***
> *Frequent switching this mode can degrade the lamp.*





Keystone

Use this to adjust for trapezoidal (keystone) distortion of the projected image.



Adjustment Method

(1) **Press the ▲ or ▼ KSTN button to make the left and right sides parallel.**
The keystone adjustment display appears when one of the buttons is pressed.



(2) **Press the CANCEL button to immediately close the display.**
The display will close when there has not been an operation in about 10 seconds.

> ***Note:***
> * *Keystone adjustment values can be saved. See "Keystone Save" on Page E-49.*
> * *Screen examples have been drawn in an exaggerated style for the purpose of description.*
> * *Please note that depending on the projected picture and the projection conditions, it may not be possible to eliminate keystone distortion completely.*

Adjustment of the Volume

This function adjusts the volume of the built-in speaker.



(1) **Press the ▲ or ▼ VOL button to adjust the volume.**
The volume adjustment display appears when one of the buttons is pressed.

The ▲ button increases the volume and the ▼ button decreases the volume.

(2) **Press the CANCEL button to immediately close the display.**
The display will close when there has not been an operation in about 10 seconds.

> ***Note:***
> * *Adjustment of the volume will not produce any sound unless an image is being projected.*

Enlargement of the Image and Video Movement

This function digitally enlarges the personal computer image and video image.



(1) Press the ZOOM button to enlarge the image.
The zoom display appears when the ZOOM button is pressed.

Each press of the ▲ button enlarges the image and each press of the ▼ button makes the image smaller (returning it to 1:1).



(No enlargement)





(Approximately 2 times enlargement)

(2) Pressing the SELECT ▲▼◀▶ buttons on the remote control at the time of the zoom operation will cause the display position to move.
(There will not be any movement when zoom is at 0.)



(Approximately 2 times enlargement)



(Movement)

(3) Press the CANCEL button to immediately close the display.
The display will close when there has not been an operation in about 10 seconds.

> ***Note:***
> *After magnifying the image, be sure to use the ZOOM button to bring the gauge value back to "0".*

The image can also be moved in the following circumstances.

- When "Aspect" is set to "Real" by the signal of the personal computer, and the input resolution is higher than the display resolution of the projector.
- When "Aspect" is set to "Zoom" by the video signal.

> ***Note:***
> ** Zoom and image movement functions are cancelled when the input is switched.*
> ** The greater the zoom enlargement, the less distinct the image will appear. The reason for this is that the dots are being digitally corrected so that they are not conspicuous.*
> ** Movement of the screen will not be possible when the menu screen is being displayed.*

Using the Presentation Timer

The presentation is given while checking the timer displayed on the screen.
The gauge display allows the remaining time to be known at a glance.



(1) Press the TIMER button to show the settings display.
The display will close when an operation has not been made for about 10 seconds.

[Timer settings display]

Press the CANCEL button to close the display immediately.

(2) Use the ◀ and ▶ SELECT buttons to set the time.
The setting contents are "Off" and from 10 to 60 minutes (in 10-minute intervals)
Settings can also be made with the SELECT ◀▶ buttons.

(3) Press the ENTER button and start the timer.
- The display of the timer setting will close, the display of the timer will appear and simultaneously the timer will start.

Gauge (Blue)

[Timer Display]

The blue gauge indicates the remaining time. When the gauge disappears,the time is up.
The gauge continues to be displayed when the timer is stopped.

When the remaining time is "0" (Gray)

- Press the ENTER button to restart the timer. The timer will start with the same time setting.
- Press the CANCEL button to close the timer display. The timer setting will return to "Off".

Moving the Position of the Timer Display
The SELECT ▲▼◀▶ buttons on the remote control permit movement within the movable range of the timer display.


Movable Range of the Timer Display

Note:
- ** The timer display will be closed while the menu or the quick menu is displayed, and while a message is displayed; however, the timer will still be operating at such times. Also, the timer will not be displayed unless a signal is being input.*
- ** While the presentation timer is being displayed, screen movement will not be possible in the zoom mode.*

Protecting the Projector with the Security Lock

A password can be registered and the security lock set in order to protect the projector from unauthorized use.

Registering the password
The password is registered using the menus. For instructions on operating the menus, see “Menu Operation Method” on E-36.



(1) Select “Security Lock” in the “Option” menu and set it to “Enable”.
The menu closes and the password registration display appears.

(2) Use the number buttons (1 to 4) to register the password.
Be sure to input a 4-digit number.
Example: Registering the password “2441”

(1) Press number button “2”. An “*” (asterisk) appears at the first place. Next press number buttons “4”, “4” and “1” in that order. Asterisks appear in all four places.



(2) Input the password again. An “*” appears when the input number matches. If there is a mistake, the asterisks turn off. Start over from step (1) above.
If the password matches, the password registration display closes.





> ***Note:***
> *To cancel the number you have input, press the CANCEL button.*
> *The asterisks disappear and the display returns to the input standby mode at the first place.*
> *To cancel the password registration mode, press the CANCEL button again. The “Password” display turns off.*

This completes password registration.
The “Password” input display appears the next time the power is turned on.

> ***Note:***
> *The numbers you have input are not displayed. Be sure to write down the password and store it in a safe place.*

If the password input display appears when the power is turned on

When a password has been registered, the “Password” input window appears on the projected image when the power is turned on. The projector continues projecting this image until the correct password is input. At this time, only the STANDBY button (power off) works. Use the procedure described below to input the registered password. For instructions on registering the password, see E-33.

Input the password using the number buttons (1 to 4).

Be sure to input the registered 4-digit number.

Example: To input the password “2441”

Press number button “2”. An “*” (asterisk) appears at the first place.

Next press number buttons “4”, “4” and “1” in that order. Asterisks appear in all four places.

If the password matches, the window turns off and the projector can be used normally.



[Password input window]

Canceling the password/Changing the password

The password is canceled and changed using the menus. For instructions on operating the menus, see “Menu Operation Method” on E-36.



Canceling the password

Select “Security Lock” in the “Option” menu and set it to “Disable”.

This clears the password and disables the security lock.

The password input display no longer appears when the power is turned on.

Changing the password

After setting “Security Lock” to “Disable” as described above, set it back to “Enable”. The menu closes and the password registration display appears.

Register the new password. See “Registering the password” on E-33.

Using the Quick Menu

This function permits frequently used adjustments to be performed quickly.
Note that the Quick Menu will not be displayed unless the signal of the connected equipment is input. Please select the input that you wish to adjust.



(1) **A press of the QUICK MENU button brings up the quick adjustment display.**
Further presses cause the adjustment display to change in sequence.
The adjustment display can be selected with use of either the SELECT ▲ or ▼ button.

(2) **Press the cursor ◀ or ▶ button to make the adjustment.**

(3) **To close the display immediately, press the CANCEL button.**
In the absence of operations for a period of about 10 seconds, the display will close automatically.

Content of Adjustments and Settings

Example: Brightness adjustment display



Brightness	**Adjusts the brightness of the image. See page E-43.**
Contrast	**Adjusts the contrast of the image. See page E-43.**
Keystone	**Corrects (vertical) keystone distortion of the screen. See page E-30.**
Volume	**This function adjusts the volume of the built-in speaker. See page E-30.**
Presentation timer	**Sets the time of the presentation timer. See page E-32.**
Quick Color Adj.	**Select the preset color mode. See page E-45.**

Menu Operation Method

- **This section describes only the menu operation method. Please see this item should you need information while performing menu operations.**
- **For information about a menu function, adjustment, or setting, please see one of the pages containing such descriptions.**
- **Adjustments and settings are made by projecting an image and adjusting to an optimum condition.**
- **The remote control should be pointed toward the remote control sensor of the projector and operated.**
- **To return the various items that have been changed via the menu to their standard values (i.e., default values at time of shipping from the factory), see "Factory Default" on Page E-55. (Some items will not return to their initial values.)**
- **The adjustment/setting items and contents will differ depending on the input selection and the adjustment/setting items that can be used with the input signal are displayed on the menu.**

Names and functions of remote control unit buttons used for menu operations



MENU button
Used for menu display and menu closure.

SELECT ▲▼◀▶ buttons
Used in the selection of menu names and item names as well as in setting and adjusting the item contents.

ENTER button
Used to enter settings.

CANCEL button
Used to return to menu name selection as well as to close the menu (and the sub menu display).

Menu Screen Names and Functions

Menu Name
This is the title of the menu.
There is a change to the title screen when the menu is selected.
The cursor moves to the selected menu name.

Cursor (Deep Blue)
This permits setting/adjustment of the item located at the cursor position.



Item Name
This is the name of the adjustment or setting.

Icon: Pressing the ENTER button displays the sub menu or setting contents.

Adjustment Bar and Settings Contents
Adjustment Bar: The increases and decreases in bar length express the adjustment condition.
Setting Contents: Displays the contents that have been set.

Adjustment Bar



Sub menu



Item Name **Settings Contents**

Performing Menu Operations

- **Only "Setup", "Options" and "Info." can be selected when no signal is being input.**
- **The menu display will close if, after pressing a button, the next button operation is not made within 30 seconds.**
- **The adjustment and the setting values are stored even when the power is switched off or the plug is disconnected from the power outlet.**
  (Note that some items are not stored.)

Preparation **Switch on the power of the connected equipment, start the play operation or another operation, and input the signal to the projector.**
Select the input that you wish to adjust.
The menu display of the description diagram depicts an example in which the "Keystone" item name is selected.

Menu Display

1 Press the MENU button to display the menu





The menu name that existed when the menu was closed previously will be displayed.

Selection of the Menu Name

2 Press the SELECT ◀▶ button to select the menu name





Each press of the SELECT ▶ button advances the selection one step in the sequence of "Color" → "View" → "Setup" → "Option" → "Info." → "Image". Each press of the SELECT ◀ button causes a return of one step.
The cursor moves to the selected menu name.

Note:
Please check that the cursor of the item name has disappeared at the time of menu name selection.
Press the CANCEL button to make the cursor disappear.

Displaying the Cursor

3 Press the ▼ SELECT button to display the item name selection cursor.





This condition allows selection of the item name.

Selection of the Item Name

4 Press the SELECT ▲▼ button to align the cursor with the item name





Items for which the ↵ Icon Is Displayed

Press the ENTER button to display the submenu.
Press the SELECT ▲▼ button and align the cursor with the desired item name.
There are also some items for which the setting display or the verification display will appear. Please see the various item descriptions.





Making Adjustments/Settings

5 Press the SELECT ◀▶ button and make the adjustment (or setting) while viewing the image

When a button is pressed, the image will also change.





Adjustment display: Each press of the button results in a change of 1 point and continued presses cause changes to proceed in order.
Setting display: The setting contents display changes with each press of the button.

Closing the Menu

6 Press the MENU button and close the menu display



Selecting Another Menu Name with Remote Control Operation

When a sub menu is displayed, press the CANCEL button and close the sub menu.
Press the CANCEL button again to turn off the item name cursor.







Press the SELECT ◀▶ button and select the menu name. (Menu names cannot be selected when the item name cursor is displayed.)





Note:
A press of the QUICK button while the menu is displayed will close the menu and display the quick menu. A press of the MENU button while the quick menu is displayed will close the quick menu and display the menu.

List of Item Names Offering Input Selection and Adjustments/Settings

The item names that can be adjusted/set will differ depending on the input signal.

[Example of Menu Display Items at the Time of Input Signal RGB Selection]



Menu name	Item Name	Sub Menu Item Name	Input Signal: Component	RGB	VIDEO	S-VIDEO	Reference Page
Image	Brightness		○	○	○	○	E-43
	Contrast		○	○	○	○	E-43
	Color				○	○	E-43
	Tint		○		○	○	E-43
	Sharpness				○	○	E-43
	Picture Adj.			○			E-43
	Fine Picture			○			E-44
	H Position			○			E-44
	V Position			○			E-44
	Reset		○	○	○	○	E-44
Color	Quick Color Adj.			○			E-45
	Gamma		○	○	○	○	E-45
	Color Temp.		○	○	○	○	E-46
	White		○	○	○	○	E-46
	Color Space		○				E-46
	White Balance			○			E-47
View	Aspect		○	○	○	○	E-48
	Filter		○	○	○	○	E-48
	Vertical Flip		○	○	○	○	E-49
	Horizontal Flip		○	○	○	○	E-49
	Keystone		○	○	○	○	E-49
	Keystone Save		○	○	○	○	E-49

“Tint” can be adjusted only at the time of NTSC composite/S signal input.



Menu name	Item Name	Sub Menu Item Name	Input Signal: Component	RGB	VIDEO	S-VIDEO	Reference Page
Setup	Auto Source		○	○	○	○	E-50
	Auto Power Off		○	○	○	○	E-50
	Menu Position		○	○	○	○	E-51
	Lamp Mode		○	○	○	○	E-51
	Input Format	RGB	○	○	○	○	E-52
		Video	○	○	○	○	E-52
		S-Video	○	○	○	○	E-52
	Presentation Timer		○	○	○	○	E-52
Option	Language		○	○	○	○	E-53
	On Screen		○	○	○	○	E-53
	Background		○	○	○	○	E-53
	Startup Screen		○	○	○	○	E-54
	Security Lock		○	○	○	○	E-54
Info.	Status		○	○	○	○	E-55
	Factory Default		○	○	○	○	E-55
	Lamp Timer Reset		○	○	○	○	E-55
	Resolution		○	○	○	○	E-56
	Frequency		○	○	○	○	E-56
	Lamp Timer		○	○	○	○	E-56

Image

- **Perform this operation while projecting the picture for which the adjustment/setting will be made.**
- **Select the menu name "Image".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Page E-41.

Brightness / Contrast / Color / Tint / Sharpness

Picture qualities such as brightness and contrast will change depending on the whether the room is bright or dark. Please adjust to suit your preference.



Select the desired item name and then adjust with the SELECT ◀▶ buttons.

Item Name	SELECT ◀ Button	SELECT ▶ Button
Brightness	Darker	Brighter
Contrast	Less contrast	More contrast
Color	Less dense color	Denser color
Tint	More red	More green
Sharpness	Softer image	Sharper image

Note:
** The adjustment values of the adjustable items are stored according to input source.*
** "Tint" can only be adjusted when inputting NTSC composite/S-Video signals or component signals.*

Picture Adj. / Fine Picture / H Position / V Position

Usually, automatic adjustment is performed at the time of signal selection, but when automatic adjustment is not effective, these adjustments can be performed.



Note:
When the image extends beyond the boundaries of the screen or is smaller than the screen, check that the "View" → "Aspect" setting is set to "Auto". See "Aspect" on Page E-48.

Picture Adj. (Picture Adjustment)

Adjust this when bright and dark vertical bands appear on the screen.



Select the "Picture Adj." item name and adjust with the SELECT ◀▶ buttons so that the vertical bands disappear and brightness becomes uniform across the screen.

Fine Picture

Adjust this when the picture shows a lack of color fidelity or flickering.

Select the “Fine Picture” item name and adjust with the SELECT ◀▶ buttons so that the lack of color fidelity or the flickering disappears.



H Position

Adjust this when the picture is shifted to the left or right.

Select the “H Position” item name and adjust with the SELECT ◀▶ buttons.



V Position

Adjust this when the picture is shifted up or down.

Select the “V Position” item name and adjust with the SELECT ◀▶ buttons.



Reset

This function resets (i.e., returns to the standard settings) the adjustment/setting value of the “Image” menu name.

A press of the ENTER button forces the reset.



Note:

- *The item name “Fine Picture” at the time of RGB input will not be reset.*
- *“Reset” of the menu name “Image” can be reset for each input source.*
- *To reset the adjustments/settings of all the menu items (while noting that there are some items that cannot be reset), see “Factory Default” on Page E-55.*

Color

- **Do the following operation while displaying the image you want to adjust or set.**
- **Select the menu name "Color".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Pages E-41.

Quick Color Adj.

Select the preset color mode.

Select the "Quick Color Adj." item name and select the setting contents with the SELECT ◀▶ buttons.

Color ..... Select this to prioritize color.
Standard ..... Select this to prioritize brightness.
* When "Color" or "Standard" is selected, the "Gamma", "Color Temp." and "White" adjustment items are displayed in gray and cannot be selected or adjusted.
Custom ..... "Gamma", "Color Temp." and "White" adjustment items can be selected and adjusted
* The selected values for the different adjustment items are stored in the memory so the desired color adjustments can be set.

Gamma

Gamma corrects the proportion of change of the dark portions from the bright portions of the input signal.
Set this to reproduce natural color tone or to distinctly project a personal computer picture in a bright conference room.



Select the "Gamma" item name and select the setting contents with the SELECT ◀▶ buttons.

Normal ..... Correction with standard settings
Natural ..... Corrects for natural color tones
Real ..... Corrects with emphasis on brightness

> ***Note:***
> *When "Color" or "Standard" is selected for "Quick Color Adj.", the "Gamma" adjustment item is displayed in gray and cannot be selected or adjusted.*

Color Temp.

The screen color is affected by the color of the illumination and other extraneous light.
This function adjusts the white, which is the reference color for video equipment, and improves the quality of color reproduction. Adjustment can also be used to enhance skin colors.

Quick Color Adj.	◀	Custom	▶
Gamma	◀	Normal	▶
Color Temp.	◀	Normal	▶
White	◀	Low	▶
White Balance		↵	

Select the item name “Color Temp.” and select the setting contents with the SELECT ◀▶ buttons.

Low ..... Produces warm whites (reddish)
Medium ..... Produces warm whites (yellowish)
Normal ..... Produces the white of sunlight
High ..... Produces cool whites (bluish)

> ***Note:***
> *When “Color” or “Standard” is selected for “Quick Color Adj.”, the “Color Temp.” adjustment item is displayed in gray and cannot be selected or adjusted. See “Quick Color Adj.” on E-45.*

White

When projecting, this function is used to emphasize the whites of text or diagrams on the personal computer.

Quick Color Adj.	◀	Custom	▶
Gamma	◀	Normal	▶
Color Temp.	◀	Normal	▶
White	◀	Low	▶
White Balance		↵	

Select the item name “White” and use the SELECT ◀▶ buttons to select the setting contents.
Select the desired degree of white from among “Low”, “Medium”, and “High”.

> ***Note:***
> *When “Color” or “Standard” is selected for “Quick Color Adj.”, the “White” adjustment item is displayed in gray and cannot be selected or adjusted. See “Quick Color Adj.” on E-45.*

Color Space

Set this function when a component signal (YPbPr) is projected and the image is extremely red or extremely green.

Gamma	◀	Normal	▶
Color Temp.	◀	Normal	▶
White	◀	Low	▶
Color Space	◀	BT.709	▶

Select the item name “Color Space” and use the SELECT ◀▶ buttons to select a color space setting that provides a normal image.

Selection contents at the time of YPbPr input
BT.709, SMPTE240

> ***Note:***
> * *When the component signal undergoes conversion processing to red, green, and blue which express the image of the projector, the correct color cannot be reproduced unless a system compliant with the color difference conversion system of the input signal is used. Color Space serves to make this selection.*
> * *The color space can only be adjusted with high definition TVs.*

White Balance

This function automatically adjusts the black level and the white level of the analog RGB input signal to suit the personal computer.

1 **Select the item name [White Balance] and press the ENTER button.**

The display will change to [Input Black Signal].

2 **The screen background color of the connected personal computer will be set to black.**

3. **Press the ENTER button. The display will change to [Adjusting Black] and the black level will be adjusted.**



4 **The adjustment of the black level is completed and the display changes to [Input White Signal].**

5 **The screen background color of the connected personal computer will be set to white.**

6 **Press the ENTER button. The display will change to [Adjusting White] and the white level will be adjusted.**



[White balance complete] is displayed for a while and the adjustment is completed.

View

- **Perform this operation while projecting the picture for which the adjustment/setting will be made.**
- **Select the menu name "View".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Page E-41.

Aspect



This function sets the horizontal and vertical picture proportions of the input signal.

Select the item name "Aspect" and select the setting contents with the SELECT ◀▶ buttons.

Personal Computer Signal

Auto ..... Automatically enlarges or reduces the image to project a full screen in a ratio of 4:3
Direct ..... Maintains the aspect ratio and projects a picture of the maximum displayable size
Real ..... Projects the input signal without pixel conversion

Video Signals

Auto ..... While maintaining the aspect ratio, projects a full screen so that no portions extend beyond the boundaries of the screen. The top and bottom of the 16:9 image becomes black.
Wide ..... Projects to fill the full width with the entire image at 16:9.
(This feature is used to project a squeezed image in a proper aspect ratio.)
Zoom ..... Projects only the 4:3 portion within 16:9 image to fill the screen.
(Portion that extend off screen is cut.)

See "Selection of Aspect Ratio" on Page E-28 for diagrams of projection screen images that correspond to the input signals.

> ***Note:***
> *Please note that using this monitor for the purpose of commercial gain or the attraction of public attention in a venue such as a coffee shop or hotel and projecting a 4:3 screen in wide mode or leaving a squeezed screen as a compressed image raises concern about the infringement of the copyright holder's rights which are protected by copyright law.*

Filter



This function sets the sharpness when the input signal is adjusted to the resolution of the projector and enlarged or reduced.

Select the item name "Filter" and select the setting contents with the SELECT ◀▶ buttons.

Smaller numerical values result in a sharper picture and larger values result in a softer picture. Please select your desired setting value.

Vertical Flip

In selecting the method of projecting to the screen, these functions are set when the projector is in a rear screen installation.

Select the item name “Vertical Flip” or “Horizontal Flip” and select the setting contents with the SELECT ◀▶ buttons.



“Vertical Flip” Off
“Horizontal Flip” Off



“Vertical Flip” Off
“Horizontal Flip” On

“Vertical Flip” On
“Horizontal Flip” On

“Vertical Flip” On
“Horizontal Flip” Off



Keystone

Keystone distortion will occur when the projector and screen are on an angle (in the vertical orientation). This function is used to correct this distortion.

Select the item name “Keystone” and correct the keystone distortion using the SELECT ◀ ▶ buttons.







Note:
- ** The menus and other on-screen displays cannot be adjusted.*
- ** Please note that depending on the projected picture and the projection conditions, it may not be possible to eliminate keystone distortion completely.*

Keystone Save

This function is used to save the keystone adjustment values.
Setting Keystone Save to on will set the previous keystone adjustment values when projecting after the power cable has been disconnected and then reconnected.

Select the item name “Keystone Save” and set with the SELECT ◀▶ buttons.



Off ..... The keystone adjustment values return to the initial values when the power cable is unplugged.
On ..... The keystone adjustment values are retained in storage even when the power cable has been unplugged.

Note:
Regardless of whether Keystone Save is set to “On” or “Off”, when projection is from the standby condition, the picture is projected using the previous keystone adjustment values.

Setup

- **Select menu name "Setup".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Page E-41.

Auto Source

The Auto Source function automatically detects the input signal when the power supply is switched on and when the input is switched.



Select the item name "Auto Source" and select the setting contents with the SELECT ◀▶ buttons.

On ..... Switches on the automatic detection function
Off ..... Switches off the automatic detection function

Signal Detection Order When On
The sequence of RGB → VIDEO → S-VIDEO is searched repeatedly.
When a signal is detected, the search is stopped and the image is projected.

Auto Power Off

This function switches off the projector power automatically when the input of the projector enters a no-signal condition.



Select item name "Auto Power Off" and select the setting contents with the SELECT ◀▶ buttons.

On ..... The power is switched off when there is no signal.
Off ..... The power is not switch off even when there is no signal.

Operation when Function is On
- The "No Signal Power Off" display appears when a no-signal condition continues for approximately 10 seconds. The power is switched off about 5 minutes after this.
- If a signal is input during the appearance of the display and an operation button other than the STANDBY button is pressed, the display is closed and the function is cancelled.



Note:
Some video decks and other equipment output a blue background or other video when playback ends. When this happens, a signal is being input to the projector and Auto Power Off is not activated.

Menu Position

This function sets the display position of the menu.

Select item name “Menu Position” and select the setting contents with the SELECT ◀▶ buttons.

..... Displays on the left side

..... Displays on the right side

Lamp Mode

Use this if the picture is projected on a small screen and the picture is too bright or when projecting images in dark rooms.

Select the item name “Lamp Mode” and select the setting contents with the SELECT ◀▶ buttons.

Eco ..... The lamp’s brightness is reduced to approximately 80%, extending the lamp’s service life.
(STATUS indicator is green)

Normal ..... The lamp brightness is set to 100% and the screen is bright.
(STATUS indicator is off)

> ***Note:***
> *Frequent switching this mode can degrade the lamp.*



STATUS Indicator



Input Format

This function is used in setting the input signals of the input connectors.
Normally, this should be set to Auto. When identification is not possible with Auto, make the setting.

Select the item name “Input Format”, press the ENTER button, and the sub menu will open.
Select the connector that is to be changed, and select the setting contents with the SELECT ◀▶ buttons.



[RGB]
This is the signal setting for the RGB connector.

Auto ..... Automatically identifies the signal.
RGB ..... Analog RGB signal is set.
Component . Component signal is set.

[Video] and [S-Video]
[Video] is the color system setting for the VIDEO connector and [S-Video] is the color system setting for the S-VIDEO connector.

Auto ..... Automatic identification.
NTSC ..... Fixed to the NTSC system.
NTSC 4.43 .. Fixed to the NTSC 4.43 system.
PAL ..... Fixed to the PAL system.
PAL M ..... Fixed to the PAL M system.
PAL N ..... Fixed to the PAL N system.
PAL 60 ..... Fixed to the PAL 60 system.
SECAM ..... Fixed to the SECAM system.

Presentation Timer

The presentation is given while checking the timer displayed on the screen.
The gauge display allows the remaining time to be known at a glance.

Select the item name “Presentation Timer” and select the setting contents with the SELECT ◀▶ buttons.

Setting contents: Off, 10 min., 20 min., 30 min., 40 min., 50 min., 60 min.

To start the timer...
Press the MENU button and open the menu.
The timer display will appear at the lower right and the timer will start.
See “Using the Presentation Timer” on Page E-32 for details.

Option

- **Select menu name "Option".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Page E-41.

Language

This function sets the language that is displayed on screen in the messages and menu displays.

Select item name "Language" and press the ENTER button to open the Language sub menu.
Select the language with the SELECT ▲▼ buttons.



On Screen

This function switches on/off the messages displayed with a black frame such as the input signal information and the aspect ratio.

Select item name "On Screen" and select the setting contents with the SELECT ◀▶ buttons.

On ..... The message is displayed.
Off ..... The message is not displayed.

> ***Note:***
> *Even when set to off, messages that are not in a black frame will be displayed.*



Example of a display when the ASPECT button is pressed



Background

This function sets the screen color when the input source is no-signal.

Select item name "Background" and select the setting contents with the SELECT ◀▶ buttons.

Blue ..... Sets a blue screen when there is no signal
Black ..... Sets a black screen when there is no signal



Startup Screen

This is the selection of whether or not to display the logo screen at startup time.

Select item name "On Screen" and select the setting contents with the SELECT ◀▶ buttons.

Logo ..... Displays the logo.
Blank ..... Does not display the logo.

> ***Note:***
> *When "Logo" is selected at the startup screen, the "PLUS" logo is displayed.*

Security Lock

A password can be registered and the security lock set in order to prevent unauthorized use of the projector.
For instructions on using the security function, see "Protecting the Projector with the Security Lock" on E-33.

Select item name "Security Lock" and select the setting contents with the SELECT ◀▶ buttons.

Disable ..... The security lock is disabled.
The projector can be operated without inputting the password.
Enable ..... The security lock is enabled.
The security lock is activated when the power is turned on, and the password must be input in order to operate the projector.

Info.

- **Select menu name "Info.".**
  See "Menu Operation Method" on Page E-36 for information about performing menu operations. The item name display will differ depending on the input signal. See "List of Item Names Offering Input Selection and Adjustments/Settings" on Page E-41.

Status

This displays information about the equipment.

Select item name "Status" and press the ENTER button.
There is a change to the status display.
Press the CANCEL button to return to the menu.

Display Contents:
Projector model, firmware version, and the internet home page address of PLUS Vision Corp.





Factory Default

This function returns the adjustments and settings of all the input sources to the standard factory default values.

Select item name "Factory Default" and press the ENTER button.
There is a change to the display [Press "ENTER" to Factory Default Set].

Press the ENTER button to initialize.
To cancel, press the CANCEL button and there will be a return to the menu.

Items that are not set to the factory default:
Projection method, Language and Lamp Timer and Security.





Lamp Timer Reset

This function resets the lamp timer. Be sure to perform the reset operation when the lamp cartridge has been replaced.

Select item name "Lamp Timer Reset" and press the ENTER button.

There is a change to the display "Press "ENTER" to Lamp Timer Reset".

Press the ENTER button to initialize.
To cancel, press the CANCEL button and there will be a return to the menu.





Resolution / Frequency

This function displays the resolution and frequency of the detected input signal.

Status	↵
Factory Default	↵
Lamp Timer Reset	↵
Resolution	1024 X 768
Frequency	60 Hz, 78KHz
Lamp Timer	1000 h

Lamp Timer

This displays the lamp timer.

Status	↵
Factory Default	↵
Lamp Timer Reset	↵
Resolution	1024 X 768
Frequency	60 Hz, 78KHz
Lamp Timer	1000 h

This projector has an Eco mode function. The lamp life will differ between Normal mode and Eco mode.

Lamp Life
Use only in Normal mode: approx.1500 hours
Use only in Eco mode: approx.2000 hours
* Lamp life will differ when there has been switching between the modes.

- **When Lamp Life Has Been Reached**
  "Replace the Lamp Cartridge" is displayed on the screen for 10 seconds in a 1-minute interval.
  Please replace the lamp with a new one.
  See "Replacing the Lamp Cartridge" on Page E-61 for information about lamp cartridge replacement.

- **When Over 100 Hours Have Elapsed Since Reaching Lamp Life (Including Eco Mode)**
  [Warning!! System Shutdown] is displayed for 10 seconds and the power is switched off. Pressing the STANDBY button under this condition will not switch on the power. Please replace the lamp cartridge.

When an Indicator is Lit or Flashing

The indicators on the projector's control panel light or flash to notify of problems, as described below.
An indicator is also used to notify you of the currently set power mode. See "Power Cable Connections and Switching the Power On/Off" on page E-22.



Indicator status	What you should do
STANDBY STATUS Lit red **When the power is on** (Lit green) **Standby** (Lit amber)	**It is time to replace the lamp.** Replace with a new lamp cartridge.
STANDBY STATUS Lit red Flashing amber for 60 seconds, then lit amber	**The lamp has reached the end of its service life. The power will no longer turn on.** The projector can be used for 100 hours after the lamp has reached the end of its service life. Replace with a new lamp cartridge.
STANDBY STATUS Flashing red (lit for 1 seconds/off for 1 seconds) Lit red	**The lamp cover is open.** The lamp cover is not properly mounted. Mount it properly.
STANDBY STATUS Flashing red (lit for 0.5 seconds/off for 0.5 seconds) Lit red	**The temperature is abnormally high.** • The temperature protector has been activated. If the room temperature is high, move the projector to a cool place. If the projector's internal temperature is high, check the cooling fan's ventilation slots and clean them if they are clogged. • When the temperature protector is activated, the power turns off and in some cases will not turn back on immediately. In this case wait about 90 seconds, then try again.
STANDBY STATUS Flashing red (lit for 0.5 seconds/off for 0.5 seconds) Lit amber	**The fan has stopped.** Unplug the power cable and contact a store that sells the V3-131/V3-111 for repairs.
STANDBY STATUS Flashing red (lit for 1 seconds/off for 1 seconds) **When the lamp has burned out during use** Flashing amber for 90 seconds, then lit amber **When the lamp does not come on from the start** Lit amber	**The lamp will not light.** Wait at least 90 seconds, then turn the power back on. If the problem persists, unplug the power cord and contact a store that sells the V3-131/V3-111 for repairs.
STANDBY STATUS Flashing amber (for several seconds) Flashing amber (for several seconds)	**The STANDBY button has been pressed with the lens stowed away.** The STANDBY indicator flashes for several seconds, then stops flashing, remaining lit, and the projector is set back to the standby status (with the STATUS indicator off). Press the lens lift button to raise the lens unit, then press the STANDBY button. The power will now turn on. **The lens unit was stowed away while an image was being projected.** The projector automatically turns off, and the indicators continue to flash for 90 seconds. (The cooling fan continues to run during this time.) To turn the projector back on, wait 90 seconds, press the lens lift button to raise the lens, then press the STANDBY button. The power turns on.

Should an indicator be in a condition other than normal or flash at a rate other than the aforementioned, disconnect the power cable and contact your store of purchase.

Thermal Protector

When the temperature inside the projector becomes abnormally high, the STATUS indicator flashes red (0.5 seconds on/0.5 seconds off), the STANDBY indicator is a steady red, and at the same time the temperature protector operates and switches off the power of the projector.
Should this happen, please take the following actions.

1. Switch off the power and disconnect the power plug from the wall outlet.

2. Check the following matters and take the required measures.
When the projector is being used in a location that has a high ambient temperature, set it up again in a cool location. Check the outflow and intake holes and clean them if they are obstructed.

3. Wait about 60 minutes until the temperature of the projector drops.
If after having performed the above matters, the problem still has not been solved, please contact your store of purchase.

Troubleshooting

Check the following matters before requesting servicing.

Problem	Check	Reference Page
Power does not turn on	• Is the power cord plugged into a power outlet? • Is the lamp cover properly mounted? • Is the projector's temperature high? To protect the projector, the power cannot be turned on when the projector's temperature is abnormally high. • Has the lamp reached the end of its service life?	E-22 E-63 E-57 E-57
No image is produced	• Is a connected input selected? • Is the cable properly connected to the input terminal? • When a computer is connected, are signals being output from the computer? • Does the signal being input have a frequency usable with this projector? • Are the brightness and contrast adjusted to the minimum? • Is the STATUS indicator lit a steady red or flashing red? • When the component signal of the DVD player is connected with the RGB connector and the image is not output, is [Input Settings] of the RGB connector properly selected? • For a RGB input, has the picture been properly adjusted?	E-27 E-17–20 E-56 E-65 E-43 E-57 E-52 E-43, 44
Image is distorted	• Is the projector properly installed? • For trapezoidal (keystone) distortion, perform keystone adjustment. Please note that depending on the projected picture and the projection conditions, it may not be possible to eliminate keystone distortion completely.	E-26 E-30, 49
Image is out of focus	• Is the lens properly focused? • Are the screen and projector installed at the proper distance? • Does the projection distance exceed the focusing range? • Is there condensation on the lens, etc.? If the projector is moved from a cool storage area to a warm place and the power is turned on, condensation may form on the lens or internal optical parts. If this happens, wait until the condensation has evaporated before using the projector.	E-25 E-14–15 E-14–15 –
Image is not in proper position and is not displayed properly	• For a computer input, are the horizontal and vertical positions properly adjusted? • Does the input signal have a compatible resolution and frequency? Check the computer's resolution.	E-44 E-65
Video image is crushed	• If the image is crushed in the horizontal or vertical direction or if it is not displayed over the entire screen, select a different aspect ratio.	E-28
Colors of the overall image are strange	• When a component signal is being input, is the color space setting proper? • For a composite input, is the tint properly adjusted?	E-46 E-43
Characters flicker or colors are offset for RGB inputs	• From the menu, select "Image" and adjust the clock frequency and phase.	E-43, 44
Cannot select the menu name	• Other than [Settings], [Option] and [Information], selection will not be possible unless a signal is being input to the projector and the image/picture is projected.	–
Remote control unit does not operate	• Are the remote control unit's batteries worn? Replace with new batteries. • Is there an obstacle between the remote control unit and the projector's remote control signal sensor? • Is the remote control unit outside of range? • Are you pointing the remote control unit's transmitter towards the projector's remote control signal sensor?	E-12 E-12 E-12 E-12
STATUS indicator is lit red or flashing red	• See "When an indicator is lit or flashing".	E-57

Cleaning

- Be certain to disconnect the power plug from the power outlet before cleaning.
- Do not spray or otherwise expose the projector, lens, or screen to volatile substances such as insecticides. Do not leave rubber or vinyl products in contact with the projector for long periods. Doing so could cause them to undergo qualitative changes or the coatings may peel, etc.

Cleaning a Soiled Projector Main Unit

- Wipe with a lint-free, soft, dry cloth.
  When very dirty, wipe with a cloth that has been moistened with a diluted neutral detergent, then finish with a dry cloth. If a chemically-treated cloth is going to be used, please follow any written warnings.
- Do not wipe with thinner, benzene, or other solvents. Doing so could cause them to undergo qualitative changes or the coatings may peel, etc.
- When removing the dust of the outflow and intake holes, use the brush attachment on a vacuum cleaner to clean out the dust. Avoid using the vacuum directly without attaching the adapter as well as the use of a nozzle adapter.
- Do not scratch or otherwise hit the projector body with your nails or other hard object, since this will cause scratches.

Dirty Lens

- Clean using the same method you would use to clean a camera lens: Use a commercial blower for camera use or cleaning paper for eye glasses. Be careful not to scratch the lens at this time.

Dust of the Intake and Outflow Holes

Dust that collects in the intake and outflow holes will obstruct the ventilation and cause the internal temperature to rise which could cause damage. Clean this area carefully. As a guideline, clean at least every 100 hours of usage.

- Switch off the power, check that the STANDBY indicator has changed to a steadily lit amber, then unplug the power cable.
- Clean out the holes from the outside using a vacuum cleaner. Use the brush adapter of the vacuum cleaner to do this. Avoid using the vacuum directly without attaching the adapter as well as the use of a nozzle adapter.



Cleaning the Inside of the Projector

Cleaning of the inside of the projector is required about once a year. Failure to clean over a long period while dust has collected inside the projector could cause a fire or breakdown. Do not clean the inside of the projector by yourself. Please be sure to contact your dealer.

Replacing the Lamp Cartridge

- **The lamp that is used as a light source in the projector has a limited service life. The rated service life of the lamp is about 1500 hours (when used in normal mode only). This could be shortened depending on conditions of use and other factors.**
  Note that lamp life will be extended when the projector is often used in Eco mode. (The rated service life of the lamp means the average value of lamp life for lamps that have been manufactured over a long period, and it is derived from test conditions at this company.)
- **When the life of the lamp is exceeded, the STATUS indicator lights a steady red and the message [Replace the Lamp Cartridge] is displayed on the screen. When this occurs, it is time to replace the lamp cartridge. Please make the replacement following the procedure below.**

- **If the projector is used another 100 hours after the lamp's service life is reached, the power is set to the standby mode and no longer turns on.**

- **Contact a store that sells the V3-131/V3-111 for a replacement lamp. Indicate you need a V3-120 replacement lamp for the V3-131/V3-111 (order code 28-051).**

⚠ CAUTION

- Replacement of the lamp cartridge is performed after switching off the power, waiting for the cooling fan to stop, disconnecting the power plug from the power outlet, and then leaving the projector for about 60 minutes before replacement is started. Replacement of the lamp cartridge during operation or immediately after operation stops will cause burns because of the high temperature.
- Do not remove any screws other than those specified.
- Do not touch the lamp with bare hands. Doing so could shorten the life of the lamp.
- If lamp has reached the end of its usable life, the lamp bulb may shatter. When this happens, an explosive sound can be heard and pieces of glass may be scattered in the lamp cartridge. Do not touch them as the pieces of glass may cause injury. If this happens, contact your dealer or the store the projector was purchased.

Replacing the Lamp Cartridge

Preparations: Turning the projector upside-down on top of a soft cloth, etc., so that it does not get scratched makes it easier to replace the lamp cartridge. Turn the projector right-side up after replacing the lamp cartridge.

1 Unplug the power cord.

2 Turn the projector upside-down.

3 Remove the lamp cover.

(1) Turn the lamp cover's set screw counterclockwise and loosen until the screw turns freely. (The screw does not come off.)



(2) Open the lamp cover a little, then pull it in the direction of the arrow and remove it.



4 Remove the lamp cartridge.

(1) Fully loosen the lamp cartridge's two screws. (The screws do not come off.)



(2) Grasp the lamp cartridge's handle and pull upward to remove the lamp cartridge.



5 Mount the new lamp cartridge.

(1) Push the lamp cartridge in slowly.
(Line it up with the screw holes in the projector.)



(2) Turn the lamp cartridge's two screws clockwise to tighten them.



6 Mount the lamp cover.

(1) Set the tip of the lamp cover in place, then close the lamp cover.



(2) Turn the lamp cover's screw clockwise to tighten it.



7 Reset the Lamp Timer.

Connect the power cable, switch on the power, and then reset.
Select [Info.] → [Lamp Timer Reset] on the menu and press the ENTER button. There is a change to the initialization verification display. Press the ENTER button again. See "Lamp Timer Reset" on Page E-55.

Note:
After reaching the lamp service life, if the lamp is used for more than another 100 hours, it will not be possible to switch on the power. Should this happen, while the projector is in the standby mode, simultaneously holding down the projector's SOURCE button and AUTO button for more than 5 seconds will clear the lamp timer. Checking that the STATUS indicator is out will show that the lamp timer has been cleared. Contact a store that sells the V3-131/V3-111 for a replacement lamp. Indicate you need a V3-120 replacement lamp for the V3-131/V3-111 (order code 28-051).

Specifications

Model	V3-131/V3-111

Optical

Method of projection :	DLP™ (single chip DMD)
DMD	**V3-131:** 0.7 inches 1024×768 dots **V3-111:** 0.55 inches 800×600 dots
Lamp	120 W high pressure mercury lamp
Projection lens :	Fixed focus, Manual focus F = 2.6, f = 23 mm (f = 0.91 inch)
Image size	**V3-131:** Minimum: 36 inch (at projection distance of 1.2m(3.9 feet)) Maximum: 300 inch (at projection distance of 10.0m(32.8 feet)) **V3-111:** Minimum: 28 inch (at projection distance of 1.2m(3.9 feet)) Maximum: 300 inch (at projection distance of 12.8m(42.1 feet))
Light Output	**V3-131:** Standard mode: 1000 lm **V3-111:** Standard mode: 800 lm
Contrast Ratio	2000:1 (Full on/off)

Electrical

Inputs	Video (NTSC3.58/NTSC4.43/PAL/PAL-N/PAL-M/PAL60/SECAM/YCbCr(NTSC, PAL)/ YPbPr(480p, 576p, 1080i, 720p)): (automatic or manual switching) RGB (Horizontal :15 to 80 kHz, Vertical 50 to 85 Hz)
Color Reproduction	Full color (16,770,000 colors)
Resolution	**V3-131:** VGA (640×480) expansion/true, S-VGA (800×600) expansion/true XGA (1024×768) true, S-XGA (1280×1024) compression **V3-111:** VGA (640×480) expansion/true, S-VGA (800×600) true XGA (1024×768) compression
Input Current	1.8 A
Power Requirement	100 - 240 V AC, 50/60 Hz
Power Consumption	175 watts (165 watts in eco mode)

Mechanical

Dimensions Excluding Stand	158 mm (W)×35 mm (H)×209 mm (D) (when stored, not including projecting parts) 6.2 in.(W)×1.4 in.(H)×8.2 in.(D) (when stored, not including projecting parts)
Weight	Approximately 1.1 kg / 2.4 lbs
Operational Temperatures	Data projector: 5° to 35°C (41° to 95°F), 30 to 85% humidity

• Specifications and design are subject to change without notice.

Table of Supported Frequency

The projector automatically identifies the signal input from the computer and selects the optimum resolution as shown on the table below.
Manual adjustments may be required for some input signals. See “Picture Adj. / Fine Picture / H Position / V Position” on page E-43, 44.

Signal		Resolution	Frequency		Video	RGB	
			Horizonral (kHz)	Vertical (Hz)		XGA	SVGA
VIDEO(NTSC)		–	15.734	60.0	○	–	–
VIDEO(PAL/SECAM)		–	15.625	50.0	○	–	–
VESA		640 × 350	31.5	70.1	–	○	○
		640 × 350	37.9	85.1	–	○	○
		720 × 350	31.5	70.0	–	○	○
		640 × 400	31.5	70.1	–	○	○
		640 × 400	37.9	85.1	–	○	○
		720 × 400	31.5	70.0	–	○	○
		720 × 400	37.9	85.0	–	○	○
		640 × 480	31.5	60.0	–	○	○
		640 × 480	37.9	72.8	–	○	○
		640 × 480	37.5	75.0	–	○	○
		640 × 480	43.3	85.0	–	○	○
		800 × 600	35.2	56.3	–	○	○
		800 × 600	37.9	60.3	–	○	○
		800 × 600	46.9	75.0	–	○	○
		800 × 600	48.1	72.2	–	○	○
		800 × 600	53.7	85.1	–	○	○
		1024 × 768	48.4	60.0	–	○	○
		1024 × 768	56.5	70.1	–	○	○
		1024 × 768	57.7	72.0	–	○	○
		1024 × 768	60.0	75.0	–	○	○
		1024 × 768	68.7	85.0	–	○	○
		1280 × 1024	64.0	60.0	–	○	–
Apple Macintosh		640 × 480	35.0	66.7	–	○	○
		823 × 624	49.7	74.5	–	○	○
		1024 × 768	60.2	74.9	–	○	○
		1152 × 870	68.7	75.1	–	○	○
HDTV	(1080i)	1920 × 1080	33.8	60.0	○	–	–
		1920 × 1080	28.1	50.0	○	–	–
	(720p)	1280 × 720	45.0	60.0	○	–	–
SDTV	(576p)	720 × 576	31.3	50.0	○	–	–
	(480p)	720 × 480	31.5	60.0	○	–	–

* The model name for XGA is V3-131 and SVGA V3-111.
* The projector does not support the ADC connector on Apple Macintosh.

○ : Supported frequency
– : Not supported frequency

V3-131
The display resolution is 1024×768 dots. When displaying a signal with resolutions other than 1024×768 dots such as 1280×1024, sizes of characters or lines may be uneven.

V3-111
The display resolution is 800×600 dots. When displaying a signal with resolutions other than 800×600 dots such as 1024×768, sizes of characters or lines may be uneven.

Cabinet Dimensions

Unit: mm (inch)



[When projecting]



PLUS Vision Corp.

20-11, Otowa 1-chome, Bunkyo-ku, Tokyo, 112-0013 JAPAN

www.plus-vision.com
email:plusvision@plus.co.jp

Iruma Factory of PLUS Vision Corp. has
ISO 9001 certification.
Certificate No. 12 100 17398 TMS

Iruma Office/Iruma Factory of PLUS Vision Corp. has
ISO 14001 certification.
Certificate No. NQE-0210118A

©2003, PLUS Vision Corp.